

CONFIDENTIAL



UNIVERSITI TUN HUSSEIN ONN MALAYSIA

**FINAL EXAMINATION
SEMESTER II
SESSION 2022/2023**

- COURSE NAME : ELECTROMAGNETIC WAVE
PROPAGATION
- COURSE CODE : BEJ31103
- PROGRAMME CODE : BEJ
- EXAMINATION DATE : JULY / AUGUST 2023
- DURATION : 3 HOURS
- INSTRUCTION : 1. ANSWER **ALL** QUESTIONS.
2. THIS FINAL EXAMINATION IS
CONDUCTED VIA **CLOSED
BOOK.**
3. STUDENTS ARE **PROHIBITED** TO
CONSULT THEIR OWN
MATERIAL OR ANY EXTERNAL
RESOURCES DURING THE
EXAMINATION CONDUCTED VIA
CLOSED BOOK.

THIS QUESTION PAPER CONSISTS OF **FIVE (5)** PAGES

CONFIDENTIAL

TERBUKA

- Q1** (a) Indicate the definition of a Transmission Line (TL) with several Guided Transmission Line examples. (4 marks)
- (b) Standing wave can be used as an indication of how many signal reflections occur in the line, i.e. voltage standing wave ratio (VSWR).
- (i) Describe the three different cases of standing waves with an appropriate figure (or graph). (4 marks)
- (ii) A 50-ohm TL is connected to a 75-ohm load at 100 MHz. Given $v_f = 0.5$, determine:
- reflection coefficient,
 - Standing Wave Ratio (SWR), and,
 - A distance of the first voltage maximum and minimum. (6 marks)
- (c) The smith chart has been introduced to reduce the tedious manipulations involved in calculating the characteristics of a transmission line by means of graphical representation.
- (i) Discuss the importance of the smith chart with several important parameters to be solved using the smith chart. (4 marks)
- (ii) A 30 m long lossless transmission line with $Z_0 = 50 \Omega$ operating at 2 MHz is terminated by a load of $Z_L = 60 + j40 \Omega$. If $v = 0.6$ on the line, find:
- Reflection Coefficient, R ,
 - VSWR, and
 - Z_{in} . (7 marks)

TERBUKA

- Q2** (a) Describe 2 types of propagation modes. (2 marks)
- (b) Waveguide is used for transporting electromagnetic (EM) waves from the source to the load which consists of a hollow, metal tube through which waves propagate.
- (i) Discuss the advantage of the waveguide over a transmission line. (4 marks)
- (ii) Describe the definition of evanescent, cutoff, and propagation with an appropriate figure/graph. (6 marks)
- (iii) A rectangular waveguide with dimensions of $a = 0.3$ m and $b = 0.1$ m operates below 15.1 GHz. How many TE and TM modes can the waveguide transmit if the guide is filled with a medium characterized by $\sigma = 0$, $\epsilon = 4\epsilon_0$, $\mu_r = 1$? Calculate the cutoff frequencies of the modes. (10 marks)
- (c) Elaborate on the function of electromagnetic cavity resonators. (3 marks)
-
- Q3** (a) Antenna is a transducer that converts a guided wave propagating on a transmission line (TL) into an electromagnetic (EM) wave propagating in an unbounded medium.
- (i) Describe the importance of a far-field in antenna transmission. (3 marks)
- (ii) List the parameters that govern radiations and impedance properties of the antenna. (2 marks)
- (iii) Describe the importance of antenna impedance matching. (4 marks)
- (b) Antenna polarization is one of the important antenna parameters.
- (i) Describe how to determine the antenna polarization. (4 marks)

TERBUKA

- (ii) A transmit antenna with a radiation resistance $R_{rad} = 72 \Omega$ and an effective antenna resistance, $R_e = 8 \Omega$, a directive gain, $G_d = 20$ and an input power $P_{in} = 100 \text{ W}$, determine:

- (a) antenna efficiency,
(b) antenna gain, G_p (Absolute and dB),
(c) radiated power in Watts, dBm and dBW, and
(d) EIRP in Watts, dBm and dBW.

(8 marks)

- (c) A 4 cm long center-fed dipole is used as an antenna at 75 MHz. The antenna wire is made of copper and has a radius of 0.4 mm. Calculate the radiation resistance and the radiation efficiency of the dipole antenna. For copper, $\mu_c \approx \mu_0 = 4\pi \times 10^{-7} \text{ H/m}$ and $\sigma_c = 5.8 \times 10^7 \text{ S/m}$.

(4 marks)

- Q4** (a) Radio wave propagation is also known as free-space propagation of electromagnetic waves or radio-frequency (RF) propagation.

- (i) Describe the 3 modes of radio wave propagation.

(2 marks)

- (ii) Discuss the importance of FRISS transmission with related formulas and equations.

(3 marks)

- (b) A 2.4 GHz microwave link consists of two identical antennas each with a gain of 30 dB. Given that the transmitter output power is 2 kW and the two antennas are 15 km apart, determine the received power.

(6 marks)

- (c) Free space loss is the loss incurred by the EM waves as it propagates in a straight line through the vacuum with no absorption or reflection of energy from nearby objects.

- (i) Calculate the free space loss for a microwave link that is 150 km apart operating at frequency of 1 GHz.

(2 marks)

- (ii) If a parabolic antenna with an effective area (or capture area) of 2 m^2 is used at both transmitter and receiver, what is the gain of the antenna at this frequency?
(2 marks)
- (iii) If the transmitter is producing a 45 dBm EIRP, calculate the received power. Assume the feeder loss is negligible, and there is no other loss in the system.
(3 marks)
- (iv) Repeat **Q4(c)(i)** for $f = 3 \text{ GHz}$. What is the effect of frequency to antenna gain and free space loss?
(3 marks)
- (v) Conclude based on your calculation and observation in **Q4(c)(iv)**.
(4 marks)

END OF QUESTIONS

TERBUKA