

UNIVERSITI TUN HUSSEIN ONN MALAYSIA

FINAL EXAMINATION **SEMESTER I SESSION 2019/2020**

COURSE NAME

: COMPUTER PROGRAMMING

COURSE CODE

: BNJ 20802

PROGRAMME CODE : BNG / BNK / BNL / BNM

EXAMINATION DATE : DECEMBER 2019 / JANUARY 2020

DURATION

: 2 HOURS

INSTRUCTION

: ANSWERS ALL QUESTIONS

TERBUKA

THIS QUESTION PAPER CONSISTS OF TEN (147) PAGES

- Q1 (a) A computer can be define as a machine that manipulate data based on a list of instructions called program. Computer consist of hardware and software. The physical part of computer is called computer hardware.
 - (i) Describe the main hardware components of a computer and include the diagram to support your explanation.

(7 marks)

- (ii) Briefly explain the following computer programming terms:
 - Operating system
 - Low-level programming language

(4 marks)

(iii) State the differences between pseudocode and flowchart

(4 marks)

(b) A written C++ code are given below:

```
#include <iostream> using namespace std;
int main()
{
    int a=5, b=7, c=9, d=3, sum=7;
    a += 5 - b;
    d = c %= 2;
    sum *= 5 % b++ + c / ++d;

    cout << "\nThe sum is \t" << sum << endl;

    cout << "\nValue a = \t" << a--;
    cout << "\nValue b = \t" << b;
    cout << "\nValue c = \t" << ++c;
    cout << "\nValue d = \t" << d;
    return 0;
}</pre>
```

Calculate the final value of a, b, c, d and sum by showing detailed calculation. Then, illustrate the output display if the program is executed on computer screen.

(10 marks)

Q2 Equations below is used to solve a mathematical problem. Answer question Q2(a) and Q2(b).

```
a=1, b =2, c = 2, y = 1
x = 2 a + 3 b * 4 c
y *= 8 b - ++c
z = x / 2 + y
```

- (a) Write a complete C++ programming code to print the output value of z for the equation.
 - (8 marks)

(b) Provide the output value of z with work path.

(7 marks)

(c) Suggest output display for the code given below.

```
Int main()
{ int i=2; float j=4;
  cout<< i++ << i << j++ << j << j+i;
}</pre>
```

(6 marks)

(d) The following program has errors.

```
#includes <iostream>
using namespace std
int processfunc(int x, int y);

int main(){
  int a,b,c,;
  cout>>"\nPlease enter two values\n";
  cin>>a;
  cin>>B;
  d=processfunc(a,b);

cout << "output = " << c;
  return 0;

int processfunc(int x, int y){FRBUKA int w; w = x * y / 2 return w;
}</pre>
```

Identify the errors and rewrite the correct program code. Use double slash to comment on the corrected coding line.

(4 marks)

- As a safety engineer in a car manufacturing company, you need to develop a simple system or program that detect or sense the car crash and immediately deploy an airbag when crash occur at the speed equal or faster than 40km/h. If an accident (crash) happen at speed slower than 40km/h, an airbag will not deploy. However, both condition of the crash will turn ON hazard light automatically. For practicality of the program development, assume crash detector as 1 when crash is detected and 0 for otherwise (no crash is detected) while airbag is 1 for an airbag deployment and 0 for no airbag deployment
 - (a) Analyze the input, output and write a simple pseudocode of based on this system (4 marks)
 - (b) Prepare the flowchart for this system.

(7 marks)

- (c) Construct the C++ program based on your flowchart in question **Q3(b)** (14 marks)
- Q4 (a) Based on the code below, anticipate and write the suitable output that will be displayed on screen.

```
#include <iostream>
using namespace std;
int main()
{
   int count = 0x0, i = 0b00001;
   while (i <100)
   {
      count = count + i;
      i++;
      cout << "\n count :" << count;
   }
return 0;
}</pre>
```

(5 marks)

- (b) Explain the function of **call by reference** in C++ program. Use C++ code as example. (10 marks)
- Using a function named Add_Number(), write a C++ program that receive input score, calculate total and average within the function and then display average score in main().

and the last of th

- END OF QUESTIONS -