



UNIVERSITI TUN HUSSEIN ONN MALAYSIA

FINAL EXAMINATION SEMESTER II SESSION 2017/2018

COURSE NAME

: COMPUTER PROGRAMMING

COURSE CODE

: BIT 10303

PROGRAMME

: 1 BIT

DATE

: JUNE / JULY 2018

DURATION

: 3 HOURS

INSTRUCTION

A) ANSWER ALL QUESTIONS.

B) PLEASE WRITE YOUR ANSWERS

IN THIS QUESTION BOOKLET

TERBUKA

THIS QUESTION PAPER CONSISTS OF NINE (9) PAGES

CONFIDENTIAL

BIT 10303

Instruction: Answer all questions.

Q1 (a) State the differences between while and do while loop.

(5 marks)

Answer:

(b) What is the output for Figure Q1(b). Explain the reason.

(5 marks)

```
#include <stdio.h>
main()
{
    int i;
    while (i)
    {
        printf(" Hi \n");
    }
    printf(" Hello\n");
    return 0;
}
```

Figure Q1(b)



BIT 10303

(c) Write the program code to display the output:

12345

1234

123

12

1

(10 marks)



BIT 10303

Q2 (a) Define the term recursive.

(5 marks)

Answer:

(b) Identify the error for program in Figure Q2(b). Write the correct program.

(5 marks)

```
#include <stdio.h>
void max(int num1, int num2);
main()
{
    int a=100, b=200, max_val;

    max_val = max(a,b);
    printf("Max value is %d\n", max_val);
    return 0;
}
void max(int num1, int num2);
{
    int result;

    if (num1 > num2)
        result = num1;
    else
        result = num2;
}
```

Figure Q2(b)



BIT 10303

(c) Write a recursive function named as AddNum(5) to sum numbers from 1 to 5. (10 marks)



CO	NFIL	ENTIAL
Q3	(a)	BIT 10303 Describe the differences between array and struct. (5 marks)
		Answer:
	(b)	Create a structure to store information about a person: name, citizenship number, birth date and salary. (5 marks) Answer:
	(c)	Write a program to find the maximum and minimum number using an array. (10 marks) Answer:



BIT 10303

Q4 (a) Write a complete program to read data from input file (**Table 1**) and calculate the average marks for each student. Write the output for **Figure Q4(a)** to the output file. (20 marks)

Table 1: Input data

Ali Bin Ahmad	50	80	89	
Lee Yau Ming	70	40	45	
Muthusamy	80	30	56	

Ujian 1	Ujian 2	Ujian 3	Purata
50	80	89	
70	40	45	
80	30	56	
	50	50 80 /0 40	50 80 89 /0 40 45

Figure Q4(a)



BIT 10303

- Q5 (a) Assume a, b and c are integer variables with a = 5 and b=3. Determine the value for each of the following statement:
 - i) c = a * --b

(2 marks)

ii) c = 27 / b++ - 16 % a

(3 marks)

Answer:

- (b) Assume x = 2, y = 5 and z = 15. Evaluate each of the following expression:
 - i) x * z < z / y

(2 marks)

ii) (x > 0) && (y < z) || (z < x)

(3 marks)



BIT 10303

(c) Write the correct program based on Figure Q5(c).

(5 marks)

```
#include <stdio.h>
main()
{    int i = 10, j = 20;
    if (i = 5) && if (j = 10)
        printf(" Have a Nice Day ");
    return 0;
}
```

Figure Q5(c)

Answer:

(d) Identify the error in **Figure Q5(d)**. For each error, suggest the solution and the output of the program.

(5 marks)

```
#include<stdio.h>
int reverse(int);
int main()
{    int no=5;
    reverse(no);
    return 0;
}
int reverse(int no)
{    if(no == 0)
        return 0;
else
        printf("%d,", no);
    reverse (no--);}
```

Figure Q5(d)

Answer:

TERBUKA

-END OF QUESTION-